



# **High-Performance Quad Comparator**

#### Overview

The LA6339 is a high-performance quad comparator that is capable of operating from a single power supply over a wide range of 2V to 36V. Because of its excellent input characteristics and low power, it can be very conveniently applied to multisignal parallel comparator circuits that require high-density assembly.


#### **Features**

- Wide supply voltage range (Single supply : 2.0 to 36.0V, dual supplies :  $\pm 1.0$  to  $\pm 18.0$ V).
- Wide common-mode input voltage range (0 to  $V_{CC}$ -1.5V).
- Open collector output enabling wired OR.
- Small current dissipation (0.8mA/V<sub>CC</sub>=5V,  $R_L$ = $\infty$ ) and low power.

# **Package Dimensions**

unit:mm

3003A-DIP14



# **Specifications**

#### **Absolute Maximum Ratings** at Ta = 25°C


Parameter	Symbol	Conditions	Ratings	Unit
Maximum supply voltage	V <sub>CC</sub> max		36	V
Differential input voltage	V <sub>ID</sub>		36	V
Common-mode input voltage	VICM		-0.3 to +36	V
Allowable power dissipation	Pd max		700	mW
Operating temperature	Topr		-30 to +85	°C
Storage temperature	Tstg		-55 to +125	°C

#### **Operating Characteristics** at Ta = 25°C, $V_{CC}=5V$


Parameter	Symbol	Conditions	Test Circuit	Ratings			Unit
				min	typ	max	Offic
Input offset voltage	V <sub>IO</sub>		1		±2	±5	mV
Input offset current	IIO		2		±5	±50	nA
Input bias current	ΙB		3		25	250	nA
Common-mode input voltage	VICM			0		V <sub>CC</sub> -1.5	V
Current drain	Icc	R <sub>L</sub> =∞	4		0.8	2	mA
Voltage gain	VG	$R_L=15k\Omega$	5		200		V/mV
Response time		$V_{RL}$ =5V, $R_L$ =5.1k $\Omega$	6		1.3		μs
Output sink current	ISINK	V <sub>IN</sub> <sup>-</sup> =1V, V <sub>IN</sub> <sup>+</sup> =0V, V <sub>O</sub> ≤1.5V	7	6	16		mA
Output saturation voltage	VOL	V <sub>IN</sub> <sup>-</sup> =1V, V <sub>IN</sub> <sup>+</sup> =0V, I <sub>SINK</sub> ≤3mA	8		0.2	0.4	V
Output leakage current	I <sub>LEAK</sub>	$V_{IN}^{-}=0V, V_{IN}^{+}=1V, V_{O}=5V$	9		0.1		nA

- Any and all SANYO products described or contained herein do not have specifications that can handle applications that require extremely high levels of reliability, such as life-support systems, aircraft's control systems, or other applications whose failure can be reasonably expected to result in serious physical and/or material damage. Consult with your SANYO representative nearest you before using any SANYO products described or contained herein in such applications.
- SANYO assumes no responsibility for equipment failures that result from using products at values that exceed, even momentarily, rated values (such as maximum ratings, operating condition ranges,or other parameters) listed in products specifications of any and all SANYO products described or contained herein.

## **Pin Assignment**




# **Equivalent Circuit (1 unit)**




## **Test Circuits**


1. Input Offset Voltage




## 2. Input Offset Current




3. Input Bias Current






$$I_B = \frac{|V_{F3} - V_{F4}|}{2R(1 + R2/R1)}$$


4. Current Drain




5. Voltage Gain




6. Response Time







7. Output Sink Current





8. Output Saturation Voltage


9. Output Leakage Current



















#### **Sample Application Circuits**

## Unit (resistance: $\Omega$ , capacitance: F)



Voltage comparator (with hysteresis)



- Specifications of any and all SANYO products described or contained herein stipulate the performance, characteristics, and functions of the described products in the independent state, and are not guarantees of the performance, characteristics, and functions of the described products as mounted in the customer's products or equipment. To verify symptoms and states that cannot be evaluated in an independent device, the customer should always evaluate and test devices mounted in the customer's products or equipment.
- SANYO Electric Co., Ltd. strives to supply high-quality high-reliability products. However, any and all semiconductor products fail with some probability. It is possible that these probabilistic failures could give rise to accidents or events that could endanger human lives, that could give rise to smoke or fire, or that could cause damage to other property. When designing equipment, adopt safety measures so that these kinds of accidents or events cannot occur. Such measures include but are not limited to protective circuits and error prevention circuits for safe design, redundant design, and structural design.
- In the event that any or all SANYO products(including technical data, services) described or contained herein are controlled under any of applicable local export control laws and regulations, such products must not be exported without obtaining the export license from the authorities concerned in accordance with the above law.
- No part of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording, or any information storage or retrieval system, or otherwise, without the prior written permission of SANYO Electric Co., Ltd.
- Any and all information described or contained herein are subject to change without notice due to product/technology improvement, etc. When designing equipment, refer to the "Delivery Specification" for the SANYO product that you intend to use.
- Information (including circuit diagrams and circuit parameters) herein is for example only; it is not guaranteed for volume production. SANYO believes information herein is accurate and reliable, but no guarantees are made or implied regarding its use or any infringements of intellectual property rights or other rights of third parties.

This catalog provides information as of April, 2000. Specifications and information herein are subject to change without notice.

This datasheet has been download from:

www.datasheetcatalog.com

Datasheets for electronics components.